

EMERGENCY RADIO – ER10



Emergency AM/FM radio with telescopic antenna for better signal reception. The unit also has LED 3 modes flashlight and SOS alarm. The device is powered by a built-in 2,000 mAh battery and can be recharged in 3 ways: via a USB-C connection, a solar panel or with a hand-cranked dynamo.



DISTRIBUTOR:

2N-Everpol Sp. z o.o. – BLAUPUNKT COMPETENCE CENTER,
02-801 WARSZAWA, ul. PUŁAWSKA 403A, POLSKA
Tel.: +48 22 688 08 00, www.everpol.pl, info@everpol.pl

EMERGENCY RADIO

Features and specification:

- AM/FM analog radio
- FM Frequency: 87.5~108.0MHz
- AM Frequency: 522 ~ 1620KHz
- Telescopic antenna (foldable/swivel)
- SOS alarm
- SOS alarm volume level: 110 dB
- LED flashlight with 3 lighting modes
- LED reading lamp
- Solar panel for charging the battery
- Solar panel size: 68 x 26 mm
- Manual battery charging system
- Built-in battery: 3.7V/2000 mAh
- Battery charge level indicator
- Power Bank function
- Output power 0.8 W RMS
- Power supply DC 5V, 1A
- USB-C for battery charging
- Battery charging time: 4 ~ 5 hours
- Battery operation time: up to 15 hours (depending on volume level)

Dimensions and weight of the device:

- Device dimensions: 145 x 70 x 54 mm
- Device net weight: 0.27 kg

Logistic data:

- Unit packaging dimensions (w x h x d): 155 x 75 x 80
- Gross weight 1 pc: 0.31 kg
- Master carton dimensions (w x h x d): 322 x 237 x 180 mm
- Master carton quantity: 12 pcs.
- Pallet quantity: 1320 pcs.

Package content:

- Radio – 1 pc.
- USB-C cable – 1 pc.
- User manual - 1 pc. (includes EN, PL, CS, SK, LT, LV, ET, HU, BG, RO, EL, HR, SL languages)
- PL warranty card - 1 pc.

EAN Code: 5901750507137

